
# **ABC-16 Spreader Indicator**

CE-09-0413-02 CE-09-0316-01







## Mounting dimension (Unit:mm)



ABC-16/ABC-16FA



ABC-16A/ABC-16F



## **Applications**

Specially design for all kinds of hoisting machinery

#### **Main Functions and features**

- Lamp body constructed of die cast aluminum, light weight, corrosion resistance, sealed, waterproof and dustproof.
- Super bright LED design, lifetime more than 100,000hrs.
- Flexible combination mode for wide application

#### **Specifications:**

Specifications.				
Operating	AC110V~AC240V/AC12V	Frequency	50Hz ~ 60Hz	
voltage	DC12V/DC24V/DC48V	Trequency		
Power	≤5W	Color	Red,yellow, green,blue, white(optional)	
Visible distance	>300m	LED Lifetime	≥100,000h	
Wiring type	Cable/plug (optional)	Own lead length	8m (customized)	
Operating temperature:	-30°C ~ +70°C	IP Protection	IP65	
Relative humidity	10% ~ 95% (no condensing )	Material	Main body : Aluminum alloy.	

## **Installation and Operation**

- Check whether the operating voltage complies with the rated voltage of the warning light
- Secure the light body on a smooth surface with enough mechanical strength using four M6 screws.
- Connect the power line according to the instruction table.
- Verify the connections of the power line, the corresponding lamp start work.

#### Wiring diagram


Wiring diagram								
Wiring type	Wiring diagram							
Cable		Red cable	Blace cable		Yellow–green			
Three-core		Red Cable			cable			
cable	AC220V	L	N		-  -			
3X0.5mm <sup>2</sup>	DC24V	DC24V+	DC24V-					
	Voltage	DC24V		AC1	AC110V-AC240V			
Plug ( Positive view )	Plug	3-	2-NC DC24V- DC24V+	•2 •3	1-NC 2-GND 3-L 4-N			


### **Notice**

- The part of material of products is PC( like lamp cover and lamp shell ), so it cannot direct or indirect touch the organic solvent, such as industrial alcohol, banana oil, isopropyl alcohol, carbon tetrachloride, cyclohexanone and so on, otherwise, the product will be
- Please read the instruction manual carefully before operation.
- Ensure that the power connection part is correct.
- If there are any questions when, please contact us.


Web: www.nanhua.com E-mail: sales@nanhua.com Add: Building 9. No.









ABC-16C(AC380V)





ABC-16E



ABC-16C Customized light 1

## **Model table**

		FL		14/ 1 L /	
Model	Combination type	Electric	Wiring type	Weight	
		current	Timing type	( kg )	
ABC-16	' General	<300mA	One 8m Three-core cable	1.5	
ABC-16A	ABC-16with	. 200 A	Four-core blug/ One	1	
	Four cable	<300mA	Three-core cable		
ABC-16B	ABC-16 with 2 lights	<500mA	Four-core blug/Two	3.8	
			Three-core cable		
ABC-16C	ABC-16 with 3 lights	<700mA	Four-core blug/Three	5.7	
			Three-core cable		
ABC-16D	ABC-16 with4 lights	<1A	Four-core blug/Four	7.6	
			Three-core cable		
ABC-16E	ABC-16 with 5 lights	<1.2A	Four-core blug/Five	9.5	
			Three-core cable		
ABC-16F	ABC-16with	<300mA		1	
	Four-core cable and		Four-core blug		
	grind glass				
ABC-16FA	ABC-16with 8m				
	cable and grind	<300mA	One 8m Three-core cable	1.5	
	glass				

# **Application**

